

## Amplifier

Maximum effective output	
STEREO or BI-AMP operation	170 W + 170 W (4 Ω, 1 kHz, JEITA)
	95 W + 95 W (8 Ω, 1 kHz, JEITA)
BTL operation	350 W (8 Ω, 1 kHz, JEITA)
Rated output	
STEREO or BI-AMP operation	125 W + 125 W (4 Ω, 1% THD, 1 kHz)
	70 W + 70 W (8 Ω, 1% THD, 1 kHz)
BTL operation	230 W (8 Ω, 1% THD, 1 kHz)
Allowable speaker impedance	
STEREO or BI-AMP operation	4–16 Ω
BTL operation	8–16 Ω
Total harmonic distortion	0.0015% (8 Ω, 1 kHz, 12.5 W, JEITA)
S/N ratio	113 dB (8 Ω, 1 kHz, IHF-A)
Frequency response	10 Hz – 50 kHz (+0 dB, –5 dB) (8 Ω, 1 W, JEITA)
Input sensitivity	
RCA connectors	0.66 V (with 8Ω output, 1% THD)
XLR connectors	1.3 V (with 8Ω output, 1% THD)
Input impedance	
RCA connectors	50 kΩ
XLR connectors	200 kΩ

## External control

Trigger input	1 (3.5mm mono mini jack)
Input level	12V, 1 mA
Trigger output (through)	1 (3.5mm mono mini jack)

## General

Power supply	
Model for Europe	AC 220–230 V, 50/60 Hz
Model for USA/Canada	AC 120 V, 60 Hz
Power consumption	
Models for Europe and USA/Canada	58 W
External dimensions (W × H × D, including protrusions)	290 × 84.5 × 271 mm (11 1/2" × 3 3/8" × 10 3/4")
Weight	4.4 kg (9 3/4 lb)
Operating temperature range	+5°C to +35°C
Operating humidity range	5% – 85% (no condensation)
Storage temperature range	–20°C to +55°C

## Included accessories

Power cord	× 1
Foot pads	× 3
Antistatic cloth for level meters	× 1
Owner's manual (this document, including warranty)	× 1
● For information about the warranty, users living in the USA and Canada should see pages 56–57 and the back cover (warranty document). Users living in Europe and other regions should see page 57.	

- Design and specifications are subject to change without notice.
- Weight and dimensions are approximate.
- Illustrations in this manual might differ slightly from production models.