



## MX-60M

### TABLETOP MODEL MIXER AMPLIFIER

This compact mixer amplifier is fitted with an integrated tuner and Bluetooth-module, it can be used for numerous commercial and residential purposes. The MX-60M is fitted with an individual volume control per input channel and is protected against short circuit and thermal overload.



*Pleasant background music and the right ambiance in the shop, the MX-60M makes it happen every day.*



output capacity 100V	60W
output capacity RMS 8Ω	60W
frequency range	80Hz - 18kHz < 0,5% THD
zones	1
direct output	4-8Ω / 70V / 100V
tone control	yes
built-in source	USB/SD FM tuner Bluetooth
line-out	built-in source, channel 2/3
MIC input	3 (1 XLR/ 2 jack 6,3 mm)
AUX input	2 RCA
priority input	1 (phoenix + contact)
priority levels	3
power supply	240V AC
power consumption	210W
dimensions (h x w x d)	76 x 270 x 230mm
weight	3,59kg

